

Für die Übertragung steht Ihnen folgender Frequenzbereich zur Verfügung:

Frequenzbereich	Bandbreite	Anzahl Frequenzen
566 - 608 MHz	42 MHz	max. 1680

Die Sender und Empfänger verfügen über jeweils 20 Kanalbänke, auf denen werksseitig Frequenz-Presets voreingestellt sind. Innerhalb einer Kanalbank sind die Frequenz-Presets untereinander intermodulationsfrei. Sie sind nicht veränderbar.

In der Kanalbank **U** können Sie in 25-kHz-Schritten Frequenzen frei einstellen und abspeichern. Diese sind unter Umständen nicht intermodulationsfrei.

Die Frequenz-Presets in den Kanalbänken **1** bis **20** sind in der Tabelle auf den Innenseiten dargestellt.

Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen

In Ihrem Land gelten möglicherweise gesonderte Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen.

Informieren Sie sich vor der Inbetriebnahme des Produktes unter folgender Adresse:

www.sennheiser.com/frequency-information

Transmitters and receivers are available in the following frequency range:

Frequency range	Bandwidth	Number of frequencies
566 - 608 MHz	42 MHz	max. 1680

Transmitters and receivers have 20 frequency banks respectively. Each of the channels in the frequency banks has been factory-preset to a frequency. These frequency presets within one frequency bank are intermodulation-free. They cannot be changed.

The frequency bank **U** allows the user to store individual frequencies which are freely selectable in 25-kHz steps. It might be that these frequencies are not intermodulation free.

The table printed inside lists the frequency presets in the frequency banks **1** to **20**.

Conditions and restrictions for using frequencies

There may be special conditions and restrictions for using frequencies in your country.

Before putting the product into operation, find the information for your country at the following address:

www.sennheiser.com/frequency-information



566 - 608 MHz

Frequenzbereich G / Frequency range G

Zusatzinformationen für Systeme der Serie evolution wireless 100 G4

Additional information for Sennheiser evolution wireless 100 G4 systems

Frequenzbereich G / Frequency range G: 566 - 608 MHz

US TV Channels

CH 30: 566 - 572 MHz	CH 31: 572 - 578 MHz	CH 32: 578 - 584 MHz	CH 33: 584 - 590 MHz
CH 34: 590 - 596 MHz	CH 35: 596 - 602 MHz	CH 36: 602 - 608 MHz	

EBU TV Channels

CH 33: 566 - 574 MHz	CH 34: 574 - 582 MHz	CH 35: 582 - 590 MHz	
CH 36: 590 - 598 MHz	CH 37: 598 - 606 MHz	CH 38: 606 - 614 MHz	

Channel	Bank 1	Bank 2	Bank 3	Bank 4	Bank 5	Bank 6	Bank 7	Bank 8	Bank 9	Bank 10
1	566.200	572.200	578.200	584.200	590.200	596.200	602.200	566.500	572.500	578.500
2	566.600	572.600	578.600	584.600	590.600	596.600	602.600	567.500	573.500	579.500
3	568.200	574.200	580.200	586.200	592.200	598.200	604.200	568.100	574.100	580.100
4	569.400	575.400	581.400	587.400	593.400	599.400	605.400	569.500	575.500	581.500
5	570.400	576.400	582.400	588.400	594.400	600.400	606.400	569.900	575.900	581.900
6	571.200	577.200	583.200	589.200	595.200	601.200	607.200	570.700	576.700	582.700
7	571.800	577.800	583.800	589.800	595.800	601.800	607.800	584.200	590.200	596.200
8	567.275	573.275	579.275	585.275	591.275	597.275	603.275	584.950	590.950	596.950
9	568.625	574.625	580.625	586.625	592.625	598.625	604.625	585.500	591.500	597.500
10	573.975	579.975	585.975	591.975	597.975	603.975	599.500	586.450	592.450	598.450
11	576.525	582.525	588.525	594.525	600.525	606.525	599.950	587.700	593.700	599.700
12	577.750	583.750	589.750	595.750	601.750	607.750	600.775	588.200	594.200	600.200

Channel	Bank 11	Bank 12	Bank 13	Bank 14	Bank 15	Bank 16	Bank 17	Bank 18	Bank 19	Bank 20
1	566.200	574.200	582.200	590.200	598.200	606.200	566.200	574.200	566.200	574.200
2	566.600	574.600	582.600	590.600	598.600	606.600	566.600	575.400	566.600	574.600
3	567.200	575.200	583.200	591.200	599.200	607.200	567.200	577.000	567.200	575.200
4	568.000	576.000	584.000	592.000	600.000	608.000	568.000	579.000	568.000	576.000
5	569.200	577.200	585.200	593.200	601.200	598.200	582.200	581.200	569.600	577.600
6	571.600	579.600	587.600	595.600	603.600	599.400	583.400	590.600	571.800	579.800
7	573.800	581.800	589.800	597.800	605.800	601.000	586.200	593.200	590.200	598.200
8	572.900	580.900	588.900	596.900	604.900	603.200	587.800	596.200	591.400	599.400
9	568.475	576.475	584.475	592.475	600.475	598.950	598.600	606.200	593.100	601.100
10	570.125	578.125	586.125	594.125	602.125	600.050	601.000	606.600	595.000	603.000
11	570.575	578.575	586.575	594.575	602.575	601.500	603.600	607.200	597.100	605.100
12	572.475	580.475	588.475	596.475	604.475	604.250	605.600	608.000	597.600	605.600